

# PTZ OPTICS PT-Broadcaster-E



## PTZ OPTICS

SKU: PT-Broadcaster-E

### Broadcast PTZ Camera Controller

The PTZ Optics PT-Broadcaster-E is a portable broadcast camera control system that supports Sony, Panasonic, Canon and other broadcast-handheld camcorders providing remote control. Achieve full speed PTZ Control with intelligent soft start and stop control. Feel safe with our built-in voltage control regulator for power protection.

## KEY FEATURES

- Supports Sony, Panasonic, Canon Cameras
- Supports VISCA, Pelco P & Pelco D control protocols
- Full speed PTZ Control, with intelligent start/stop
- Up to 255 Presets
- Supports Ceiling Mounting

## WHAT'S IN THE BOX

- Portable Camera Controller
- Power Supply
- Instruction Manual
- Connection Cables

### Supports Camera Types

#### Supported Camera Types:

SONY PXW-X20
SONY PXW-EX280
SONY PXW-X260
SONY PXW-EX1(R)
Most models with 8-pin mini

#### Supported Controllers:

Panasonic Controllers: AW-RP605, AW-RP555MC, AW-RP655MC

Sony Controllers: RM-BR3000 and switcher with control functions (such as AWS-G500).

VISCA Protocol Controller, Pelco-P/D Controller

### Pan & Tilt Movement

Rotation Range	340°
Rotation Speed	Level: .01 ~25°/S; Vertical: 0.1~20°/S
Presets	255 Presets

### Additional Support

Remote Switch	Supported
Power Supply Module	Supported
External Power Supply	Supported
Decoder	Built-in higher performance de-coder
Controller Distance	1200 Meters Max
Max Load	Side Load: 11lbs Top Load: 6lbs
Control Interface	RS-485, RS-422

### Electrical Index

Power Supply	15W Consumption (w/o camera)
Input Voltage	AC/DC 15~24 (3 A)

### Physical Specifications

Dimensions	6.2" x 5.9" x 10.6"
Weight	8.8 lbs.